# HP Neverstop Laser 1000 Printer series



## Ultimate printing freedom. World's first cartridge-free laser printer.<sup>1</sup>

Easily print at high volumes with the world's first cartridge-free laser printer<sup>1</sup> – includes 5,000 pages of toner.<sup>2</sup> Count on HP quality at an ultra-low cost. Print and scan virtually anywhere with HP Smart – best-in-class mobile print app.<sup>3,4</sup>



HP Neverstop Laser 1000a



HP Neverstop Laser 1000w

### **Highlights**

- Up to 20ppm mono printing
- · 5,000 pages of toner inbox
- Self Re-loadable toner
- · Wireless printing with WiFi direct (w model only)
- HP Smart App compatible
- High Speed USB 2.0 Connectivity
- 150 sheet input capacity
- · Ethernet connectivity (n model only)

#### Up to 5000 pages right out of the box before your first reload<sup>2</sup>

- Engineered for high-volume printing get 5,000 pages of toner right out of the box.<sup>2</sup>
- Get print speeds up to 20 ppm.<sup>5</sup>
- Change paper less often with a 150-sheet capacity paper tray.

#### Original HP Toner quality. Save up to 80% on HP toner.<sup>6</sup>

- Count on getting consistently high quality prints with this revolutionary laser.
- Produce sharp text and bold blacks.
- HP's innovative laser printer helps you to print at high volumes for an ultra low cost.

#### 15-second, mess-free self reload<sup>7</sup>

- Easy reload your toner with a mess-free experience.<sup>8</sup>
- Quickly and easily restore toner levels with the toner reload kit.<sup>9</sup>

#### Freedom to work anywhere

- Quickly access and print documents and images on your smartphone, from Dropbox and Google Drive.<sup>3</sup>
- Get high-quality scanning, and share to Dropbox, Google Drive, email, or the cloud virtually anywhere.<sup>3</sup>
- Get notifications when printing, scanning, or copying from your smartphone.<sup>3</sup>
- Connect your smartphone or tablet directly to your printer and easily print without accessing a network.  $^{\rm 10}$

## **Product walkaround**

#### HP Neverstop Laser Printer 1000w shown

- 1.3 LED display
- 2. 100 sheet output bin
- 3. Hi-Speed USB 2.0 port
- 4. 20 ppm
- 5. Built-in wireless networking, Built-in Ethernet (n model only), Wi-Fi Direct printing (w model only)  $\,$
- 6. 150 sheet input tray
- 7. Pre-installed Original HP Toner delivers up to 5,000 pages



## Series at a glance



| Model                           | HP Neverstop Laser 1000a | HP Neverstop Laser 1000n | HP Neverstop Laser 1000w |
|---------------------------------|--------------------------|--------------------------|--------------------------|
| Product number                  | 4RY22A                   | 5HG74A                   | 4RY23A                   |
| Functions                       | Print                    |                          |                          |
| Memory/processor                | 32MB/500MHz              |                          |                          |
| Control panel                   | 3 LED                    |                          |                          |
| Mobile printing                 | Not available            |                          | HP Smart app             |
| Connectivity                    | USB                      | USB, Ethernet            | USB, Wi-Fi               |
| Recommended monthly page volume | 250–2,500 pages          | 250-2,500 pages          | 250–2,500 pages          |
| Print speed                     | 20 ppm                   |                          |                          |

## Accessories, Supplies and Support

| Supplies            | W1103A HP 103A Black Original Neverstop Laser Toner Reload Kit (2,500 pages)   |  |  |  |
|---------------------|--|--|--|--|
|                     | W1103AD HP 103AD Dual Pack Black Original Neverstop Laser Toner Reload Kit (Per kit: 2,500 pages)  |  |  |  |
|                     | W1104A HP 104A Black Original Laser Imaging Drum (20,000 pages)  |  |  |  |
| Service and Support | UB4Z7E HP 3 year Standard Exchange Service for Neverstop Laser 1000 UB4Z4E HP 3 year Next Business Day Exchange Service for Neverstop Laser 1000 |  |  |  |

# Technical specifications

| Model                           | HP Neverstop Laser 1000a  | HP Neverstop Laser 1000n  | HP Neverstop Laser 1000w  |  |  |
|---------------------------------|---|---|---|--|--|
| Product number                  | 4RY22A  | 5HG74A  | 4RY23A  |  |  |
| Functions                       | Print   |   |   |  |  |
| Control panel                   | LED   |   |   |  |  |
| Print                           |   |   | _   |  |  |
| Print technology                | Laser   |   |   |  |  |
| Print speed <sup>T</sup>        | Black (A4, normal) Up to 20 ppm;  |   |   |  |  |
| First page out <sup>2</sup>     | Black (A4, ready): As fast as 7.6 sec;<br>Black (A4, sleep): As fast as 14 sec;                         | Black (A4, ready): As fast as 8.5 sec;<br>Black (A4, sleep): As fast as 15 sec;                           | Black (A4, ready): As fast as 7.6 sec;<br>Black (A4, sleep): As fast as 14 sec;                         |  |  |
| Print resolution                | Black (best): Up to 600 x 600 x 2 dpi;<br>Technology: 600 x 600 dpi;                                    |   |   |  |  |
| Monthly duty cycle <sup>3</sup> | Up to 20,000 pages A4; Recommended monthly page volume <sup>4</sup> : 250 - 2,500 pages                 |   |   |  |  |
| Printer smart software features | HP Auto-On/Auto-Off, HP Smart App   | Apple AirPrint™, Mopria-certified, HP Auto-On/Auto-<br>Off, HP Smart App, HP Smart Task                   | Apple AirPrint™, Mopria-certified, HP Auto-On/Auto-<br>Off, Wi-Fi Direct, HP Smart App                  |  |  |
| Standard print languages        | PCLmS; URF; PWG   |   |   |  |  |
| Print area                      | <b>Print margins</b> Top: 2 mm, Bottom: 2 mm, Left: 2 mm, Right: 2 mm; Maximum print area: 216 x 297 mm | <b>Print margins</b> Top: 2 mm, Bottom: 2 mm, Left: 2 mm, Right: 2 mm; Maximum print area: 216 x 355.6 mm | <b>Print margins</b> Top: 2 mm, Bottom: 2 mm, Left: 2 mm, Right: 2 mm; Maximum print area: 216 x 297 mm |  |  |
| Duplex printing                 | Manual (driver support provided)  |   |   |  |  |

| Model                                   | HP Neverstop Laser 1000a   | HP Neverstop Laser 1000n   | HP Neverstop Laser 1000w  |
|---|--|--|---|
| Product number                          | 4RY22A   | 5HG74A   | 4RY23A  |
| Processor speed                         | 500 MHZ  |  | <u> </u>  |
| Connectivity                            | <u> </u>   |  |   |
| Standard                                | Hi-Speed USB 2.0 port  | Hi-Speed USB 2.0 port; Fast Ethernet 10/100 Base   | Hi-Speed USB 2.0 port; Built-in Wi-fi 802.11b/g/n   |
| Wireless                                | No   |  | Yes   |
| Mobile printing capability <sup>5</sup> |  | Apple AirPrint™; Google Cloud Print™; HP Smart App<br>and other mobile Apps; Mopria™ Certified; Wi-Fi®<br>Direct printing  | Apple AirPrint™; Google Cloud Print™; HP Smart App;<br>Mopria™ Certified; Wi-Fi® Direct printing  |
| Network capabilities                    |  | 10/100/1000 Base-TX Networking   |   |
| Memory                                  | Standard: 32 MB; Maximum: 32 MB  |  |   |
| Media handling                          |  |  |   |
| Number of paper trays                   | Standard: 1 input tray; Maximum: 1 input tray  |  |   |
| Media types                             | Plain paper; Heavy paper; Bond paper; Label; Light paper; Envelope   |  |   |
| Media size                              | Custom (metric): 1.05 x 148.5 to 215.9 x 356 mm;<br>Supported (metric): A6; A5; A4; No. 10 envelope; C5<br>envelope; DL envelope; B5 (JIS); 105 x 148.5 to<br>215.9 x 297 mm | Custom (metric): 105 x 148.5 to 216 x 356 mm;<br>Supported (metric): A6; A5; A4; No.10 Env; C5 Env;<br>DL Env; B5(JIS), Oficio 216x340; 105 x 148.5 to 216<br>x 356 mm | Custom (metric): 105 x 148.5 to 215.9 x 356 mm;<br>Supported (metric): A6; A5; A4; No. 10 envelope; C5<br>envelope; DL envelope; B5 (JIS); 105 x 148.5 to<br>215.9 x 297 mm |
| Media handling                          | Standard input: 150 sheet input tray<br>Standard output: 100 sheet output bin  |  |   |
| Media weight                            | 60 to 120 g/m²;  |  |   |
| Input capacity                          | Tray 1: Sheets: 150; Envelopes: 1 Maximum: Up to 150 sheets  |  |   |

| Model                                       | HP Neverstop Laser 1000a   | HP Neverstop Laser 1000n   | HP Neverstop Laser 1000w   |  |  |
|---|--|--|--|--|--|
| Product number                              | 4RY22A   | 5HG74A   | 4RY23A   |  |  |
| Output capacity                             | Standard: Up to 100 sheets Maximum: Up to 100 sheets   |  |  |  |  |
| Compatible operating systems <sup>11</sup>  | Windows® 10, 8.1, 8, 7: 32/64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Apple®OS X EI Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13), 1.5 GB available hard disk space, Internet required, USB; Linux: for more information, see https://www.developers.hp.com/hp-linux-imaging-and-printing    |  |  |  |  |
| Compatible network operating systems        | Windows® 10, 8.1, 8, 7: 32/64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Apple®OS X El Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13), 1.5 GB available hard disk space, Internet required, USB; Linux: for more information, see https://www.developers.hp.com/hp-linux-imaqing-and-printing    |  |  |  |  |
| Minimum system requirements                 | Windows: Windows® 10, 8.1, 8, 7: 32/64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Mac: Apple®OS X EI Capitan (v10.11), macOS Sierra (v10.12), macOS High Sierra (v10.13), 1.5 GB available hard disk space, Internet required, USB   |  |  |  |  |
| Software included                           | For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HF Connected), Device Setup & Software, online user manuals, HP Printer Assistant, HP Product Improvement Study; For Mac OS: Welcome Screen (directs users to http://www.hp.com or OS App Source for LaserJet Software) |  |  |  |  |
| Printer management                          | HP Printer Assistant (UDC); HP Device Toolbox; HP Utility (Mac)  |  |  |  |  |
| Dimensions and weight                       |  |  |  |  |  |
| Printer dimensions (W x D x H) <sup>2</sup> | Minimum 380.5 x 293.4 x 211 mm; Maximum: 380.5   | x 465 x 445 mm;  |  |  |  |
| Package dimensions (W x D x H)              | 475 x 290 x 420 mm   |  |  |  |  |
| Printer weight <sup>4</sup>                 | 6.93 kg  | 6.95 kg  |  |  |  |
| Package weight                              | 8.7 kg   | 8.9 kg   | 8.7 kg   |  |  |
| Operating environment                       | Temperature: 15 to 32.5°C; Humidity: 30 to 70% RH  |  |  |  |  |
| Storage conditions                          | Temperature: -20 to 40°C;  | Temperature: -20 to 50°C;  | Temperature: -20 to 40°C;  |  |  |
| Acoustics <sup>6</sup>                      | Acoustic power emissions: 6.5 B(A); Acoustic pressure  | e emissions: 51 dB(A)  |  |  |  |
| Power <sup>7</sup>                          | Requirements: 220V - 240V nominal at +/-10% (min 198V, max 264V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Consumption: 365 watts (active printing), 2.8 watts (ready), 0.6 watts (sleep), 0.1 watts (manual off); Typical Electricity Consumption (TEC) <sup>3</sup> : Energy Star: 0.710 kWh/Week; Power supply type: Internal (built-in) Power Supply;                     | Requirements: 220V - 240V nominal at +/-10% (min 198V, max 264V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Consumption: 307 watts (active printing), 5.3 watts (ready), 0.93 watts (sleep), 0.1 watts (manual off); Typical Electricity Consumption (TEC): Energy Star version 3.0: 0.297 kWh/Week; Blue Angel: 0.69 KWh/Week; Power supply type: Internal (built-in) Power Supply; | Requirements: 220V - 240V nominal at +/-10% (mir 198V, max 264V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Consumption: 365 watts (active printing), 2.8 watts (ready), 0.6 watts (sleep), 0.1 watts (manual off); Typical Electricity Consumption (TEC) <sup>8</sup> : Energy Star: 0.710 kWh/Week; Power supply type: Internal (built-in) Power Supply; |  |  |
| Energy savings feature technology           | HP Auto-On/Auto-Off Technology   | ,  |  |  |  |
| Certifications                              | EN 61000-3-2:2014, EN 61000-3-3:2013,<br>EN55024:2010, EN 5503:2012/AC:2013, ICES-003<br>Issue 5, CISPR22:2008, CISPR32:2012, other EMC<br>approvals as required by individual countries   | EN 61000-3-2:2014, EN 61000-3-3:2013,<br>EN55024:2010, EN 55032:2012/AC:2013, ICES-003<br>Issue 5, CISPR22:2008, other EMC approvals as<br>required by individual countries  | EN 61000-3-2:2014, EN 61000-3-3:2013,<br>EN55024:2010, EN 55032:2012/AC:2013, ICES-003<br>Issue 5, CISPR22:2008, CISPR32:2012, other EMC<br>approvals as required by individual countries  |  |  |
| Blue Angel compliant                        | Yes, Blue Angel DE-UZ 205—only ensured when using Original HP supplies   |  |  |  |  |
| Country of origin                           | Made in China  |  |  |  |  |
| What's in the box <sup>9</sup>              | HP Neverstop Laser 1000a Printer; HP Black Original<br>Imaging Drum (5,000 pages yield, 20,000 pages<br>useful life); Reference guide; Setup guide; Regulatory<br>flyer; Support flyer; Warranty guide; Power cord   | HP Neverstop Laser M1000w Printer; Preinstalled;<br>HP Black Original Imaging Drum (~5000 pages yield,<br>~20000 pages useful life); Reference guide; Setup<br>guide: Regulatory flyer; Support flyer; EU declaration<br>flyer (EU only); Warranty guide; Power cord; USB<br>cable   | HP Neverstop Laser 1000w Printer; Preinstalled; HP<br>Black Original Imaging Drum (5,000 pages yield,<br>20,000 pages useful life); Reference guide; Setup<br>guide; Regulatory flyer; Support flyer; EU declaration<br>flyer; Warranty guide; Power cord; USB cable   |  |  |
| Warranty                                    | One-year limited hardware warranty. For more info, please visit us at https://www.support.hp.com   | HP one year hardware limited warranty. For full terms and conditions visit: http://www.hp.com/go/orderdocuments.   | One-year limited hardware warranty. For more info, please visit us at https://www.support.hp.com   |  |  |

#### Footnotes

- <sup>1</sup> Constant toner self-reload using imaging-drum-in-place OEM toner supplies compared to majority of worldwide competing OEM monochrome laser printers <€250 and MFPs priced <€350 as of Nov 15, 2018. HP internal research & Keypoint Intelligence-Buyers Lab 2018 study commissioned by HP. Market share as reported by IDC CYQ4 2018 Hardcopy Peripherals Tracker, 2018 Q4 Release. For details, see http://www.keypointintelligence.com/HPNeverstop.
- Actual yield varies considerably based on content of printed pages and other factors. Average based on ISO/IEC 19752 and continuous printing. For details see http://www.hp.com/go/learnaboutsupplies.
- <sup>3</sup> Requires the HP Smart app download. For details on local printing requirements see http://hp.com/go/mobileprinting.
- 4 Compared to majority of OEM mobile printing apps for inkjet, laser printers, all-in-ones for home, and home office, priced less than or equal to €429.99. Market share as reported by IDC CYQ2 2018 Hardcopy Peripherals Tracker. Claim based on lab testing and research of printer manufacturer's mobile print apps and Keypoint Intelligence - Buyers Lab study commissioned by HP. See Sept 2018 report at http://www.keypointintelligence.com/HPSmartApp. 
  <sup>5</sup> Excludes first set of test documents. For more information, see http://hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- 6 Based on internal HP comparison of MSRP/(MRSP for EMEA region) and cost-per-page of in-class HP LaserJet Pro M15 and HP LaserJet Pro MFP M28 with standard-fill HP 44A/48A Black Original LaserJet Toner Cartridge, as of March 2019. For details see http://www.hp.com/go/learnaboutsupplies.
- <sup>7</sup> HP internal research and Keypoint Intelligence-Buyers Lab 2018 study commissioned by HP. For details see http://www.keypointintelligence.com/HPNeverstop.
- <sup>8</sup> When used in accordance with set up instructions.
- <sup>9</sup> Toner reload kit is not included with the printer, please purchase separately
- 10 Mobile device needs to be connected to Wi-Fi Direct® signal of a Wi-Fi Direct supported AiO or printer prior to printing. Details at http://www.hp.com/qo/mobileprinting. Wi-Fi Direct® is a registered trademark of Wi-Fi Alliance®.

#### Technical specifications disclaimers

- 1 Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and
- <sup>2</sup> Measured using ISO/IEC 17629. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity
- <sup>3</sup> Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.
- 4 HP recommends that the number of printed pages per month be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period.
- <sup>5</sup> Apple AirPrint mobile device must have AirPrint®. Wireless operations are compatible with 2.4 GHz operations only. Learn more at http://www.hp.com/go/mobileprinting. Google Cloud Print™ 2.0 requires Google Cloud Print™ registration and Google account. Wireless operations are compatible with 2.4 GHz operations only. Learn more at http://www.hp.com/go/mobileprinting. 6 Configuration tested: Wireless model, simplex printing, A4 paper at an average of 20 ppm.
- Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device.
- B Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115 V device.
- 9 HP Black Original Laser Imaging Drum (introductory 5,000 page black toner yield provided, with 20,000 page Imaging Drum useful life). Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies.
- 11 Not supporting Windows® XP (64-bit) and Windows Vista® (64-bit). Not all "Compatible Operating Systems" are supported with INBOX software; Full solution software available only for Windows 7 and newer; For Windows Server 2008 R2 64-bit, 2012 64-bit, 2012 R2 64-bit, 2012 R2 64-bit, 2016 64-bit only print driver is installed. Windows RT OS for Tablets (32 & 64-bit) uses a simplified HP print driver built into the RT OS; Linux systems use in-OS HPLIP software.

#### http://www.hp.com/uk

© Copyright 2020 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.



