## HP LaserJet MFP M141w Printer



# The world's smallest multifunction laser in its class<sup>1</sup> designed for efficient performance.

An efficient, high-quality multifunction laser printer that fits your space. Get fast printing from the world's smallest laser in its class,<sup>1</sup> plus the time-saving HP Smart app.<sup>2,3</sup> Count on professional-quality laser printing and seamless setup.



This printer is intended to work only with cartridges that have a new or reused HP chip, and it uses dynamic security measures to block cartridges using a non-HP chip. Periodic firmware updates will maintain the effectiveness of these measures and block cartridges that previously worked. A reused HP chip enables the use of reused, remanufactured, and refilled cartridges. More at: Learn more at: <a href="http://www.hp.com/learn/ds">http://www.hp.com/learn/ds</a>

**Print Resolution:** Technical Feature 02 (statement): Black (best): Up to  $600 \times 600$  dpi

Scan Resolution: Hardware: Up to 600 ppi; Optical: Up to 600 ppi Copy Resolution: Black (text & graphics): 600 × 400 dpi Standard Connectivity: 1 Hi-Speed USB (compatible with USB 2.0 specifications); 802.11b/g/n (2.4 GHz) Wi-Fi radio + BLE Mabile Despiliting Compatibility (Despited App: Apple Apple Apple)

Mobile Printing Capability: HP Smart App; Apple AirPrint™; Mopria™ Certified; Wi-Fi® Direct Printing

Duty cycle: Monthly (A4): Up to 8,000 pages

Display: ICON LCD; LED Paper Handling: 150-sheet input tray; 100-sheet output bin



#### The world's smallest multifunction laser in its class<sup>1</sup>

- The world's smallest multifunction laser in its class<sup>1</sup> designed for efficient performance.
- Easy copy both sides of ID cards, or other small-size documents, onto the same side of one sheet of paper.
- Easily handle tasks and get a lot from one device print, scan, and copy.
- Get wireless with self-reset to help you stay connected.<sup>1</sup>

#### Productivity from your phone

- Get high-quality scanning, and share to Dropbox, Google Drive or cloud from your phone with HP Smart app.<sup>2</sup>
- Quickly access and print documents on your smartphone, from Dropbox and Google Drive, using HP Smart app.<sup>2</sup>
- With HP Smart app, take a photo as a copy, and send it to your printer from your smartphone.<sup>2</sup>
- Eliminate steps in repetitive tasks with Shortcuts.<sup>2</sup> Scan to the cloud, email, and more in just a tap.<sup>2</sup>

#### Trusted quality and convenience

- Count on getting consistently superb prints from a small laser, using Original HP Toner Cartridges.
- Simple setup with HP Smart app. It guides you through each step to seamlessly connect from any device.<sup>2</sup>
- Get connected and start printing. Easily connect your printer to your computer with the built-in USB port.  $^{\rm 8}$
- Start printing right away. The simple LED with buttons helps you complete
  projects quickly and easily.

#### Help save resources without sacrificing performance

- HP Auto-On/Off Technology intelligence can turn your printer on when you need it and off when you don't.<sup>7</sup>
- This HP Laser Jet meets ecolabel requirements, including ENERGY STAR<sup>®</sup>
- Help stop deforestation and protect forests and wildlife using HP FSC<sup>®</sup>-certified paper.

### HP LaserJet MFP M141w Printer Technical specifications

| Functions                               | Print, copy, scan   |
|---|---|
| Print speed black                       | A4: Up to 20 ppm; First page out: As fast as 8.5 sec  |
| Print resolution                        | Black (best): Up to 600 × 600 dpi   |
| Print technology                        | Laser   |
| Print resolution<br>technologies        | HP FastRes 600  |
| Print cartridges number                 | 1 (black)   |
| Standard print languages                | PCLm/PCLmS; URF; PWG  |
| Printer smart software<br>features      | HP Auto-On/Auto-Off <sup>1</sup> , HP Smart App <sup>2</sup>  |
| Scan type / Technology                  | Flatbed CIS   |
| Scan resolution                         | Hardware: Up to 600 ppi; Optical: Up to 600 ppi   |
| Scan file format                        | JPG, RAW (BMP), PNG, TIFF, PDF  |
| Scan input modes                        | Scanning via HP LaserJet Software Scan or TWAIN-compliant or WIA-compliant software   |
| Scan size maximum                       | ; Flatbed: 216 to 297 mm  |
| Scanner advanced features               | No  |
| Bit depth / Grayscale levels            | 24 bit/256  |
| Copy speed black                        | Copy speed: Up to 20 cpm  |
| Copy resolution                         | Black (text and graphics): 600 × 400 dpi  |
| Maximum number of copies                | Up to 99 copies   |
| Copier settings                         | Number of Copies; Lighter/Darker; Optimize; Paper   |
| Copier resize                           | 25 to 400%  |
| Standard connectivity                   | 1 Hi-Speed USB (compatible with USB 2.0 specifications); 802.11b/g/n (2.4 GHz) Wi-Fi radio + BLE  |
| Wireless capability                     | Yes   |
| Mobile printing capability <sup>6</sup> | HP Smart App; Apple AirPrint™; Mopria™ Certified; Wi-Fi® Direct Printing  |
| Memory                                  | Standard: 64 MB; Maximum: 64 MB Flash ROM; 64MB DDR1; 32 KB NVRAM   |
| Processor speed                         | 500 MHz   |
| Duty cycle                              | Monthly A4: Up to 8,000 pages   |
| Recommended monthly<br>page volume      | 100 to 1000   |
| Media types supported                   | Plain paper, envelope, postcard, label  |
| Media weight supported                  | 65 to 120 g/m <sup>2</sup>  |
| Media sizes supported                   | A4; A5; A6; envelopes (C5, DL); custom  |
| Media Sizes Custom                      | 105 x 148 to 216 to 355.6mm   |
| Paper handling                          | Input Capacities: Up to 150 sheets Standard; Up to 10 envelopes<br>Output Capacities: Up to 100 sheets Standard<br>Duplex Options: No<br>Standard paper trays: 1 input tray |

| What's in the box                       | 7MD74A HP LaserJet MFP M141w Printer; HP 150A Black LaserJet Toner Cartridge;<br>Power Cord; Setup Poster; Reference Guide; Warranty Guide & Flyer   |
|---|--|
| Replacement cartridges <sup>4</sup>     | HP 150A Black Laser Jet Toner Cartridge (~975), W1500A   |
| Product dimensions                      | <b>W x d x h:</b> 360 x 264 x 197 mm (14.2 x 10.4 x 7.8 in);<br><b>Maximum:</b> 360 x 427 x 347 mm (14.2 x 16.8 x 13.7 in)   |
| Product weight                          | 5.39 kg (11.86 lbs)  |
| Warranty features                       | One-year limited warranty  |
| Energy star certified                   | No   |
| Blue Angel Compliance                   | Yes, Blue Angel DE-UZ 205—only ensured when using Original HP supplies   |
| Control panel                           | 8 buttons (Power, Cancel, Copy, ID Copy, Wireless, Copy setting, Up, Down), 4 LEDs<br>(Ready/Power, Error, Toner, Wireless)  |
| Display description                     | ICON LCD; LED  |
| Software included                       | No CD in box. Download software from hp.com or 123.hp.com  |
| Compatible operating<br>systems         | From 123.hp.com: HP Smart for Windows 11, 10, Mac, Mobile (Android and iOS); HP<br>Easy Start for Windows 7; From hp.com: Full-solution software and drivers (with<br>installer): Basic-solution software and drivers; HP Easy Start; Product Documentation<br>and Support; HP Print and Scan Doctor; From Mobile OS: See "HP Mobile Printing"<br>(www.hp.com/go/mobileprinting); From In-OS app stores: HP Smart; HP Print Service<br>Plugin; From hp.com for printer administrators: Linux Print Drivers; HP Beab<br>Software (HP WS Proxy Agent); ReadIris Software |
| Compatible network<br>operating systems | Windows Server 2008 R2 64-bit, Windows Server 2008 R2 64-bit (SP1), Windows<br>Server 2012 64-bit, Windows Server 2012 R2 64-bit, Windows Server 2016 64-bit;<br>Linux (For more information see http://developers.hp.com/hp-linux-imaging-and-<br>printing)   |
| Minimum system<br>requirements          | PC: Microsoft® Windows® 11, 10, 7 SP1: 32-bit or 64-bit, 2 GB available hard disk space<br>Internet connection, Microsoft® Internet Explorer or Edge; Mac: Apple® macOS Catalina<br>(v10.15) macOS Big Sur (v11.10) macOS Monterey (v12.0); 2 GB HD; Internet required   |
| Power                                   | Power supply type: Power requirements are based on the country/region where the<br>printer is sold. Do not convert operating voltages. This will damage the printer and void<br>the product warranty; Power requirements: 110V - 127V nominal @ +/-10% (min 99V,<br>max 140V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz), 220V - 240V nominal (@<br>+/-10% (min 198V, Max 264V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz). Not<br>dual voltage, power supply varies by part number with # Option code identifier; Power<br>consumption:                     |
| Acoustics                               | Acoustic power emissions: 6.2 B(A)   |
| Operating environment                   | Operating temperature range: 15 to 32.5°C; Recommended operating temperature:<br>17.5 to 25°C; Storage temperature range: -20 to 60°C; Non-operating humidity range:<br>Operating humidity range: 10 to 80% RH; Recommended humidity operating range: 30<br>to 70% RH  |

#### Learn more at

hp.com

<sup>1</sup> HP Auto-On/Auto-Off Technology capabilities subject to printer and settings: may require a firmware upgrade. <sup>2</sup> Requires the HP Smart app download. For details on local printing requirements see www.bp.com/go/mobileprinting. Certain features/software are available in English language only, and differ between desktop and mole applications. Instant this subscription may be required. Instant this not available in a locarities. See details at www.bp.com/go/mobileprinting. Certain features/software are available in a constance with sparse of the carringe inductade with your printer, actual with any are printed and other factors. <sup>9</sup> Deckared diversations are complexed lense? The vield information on the carringe inductade with your printer, actual with any entry inter and sparse printed and other factors. <sup>9</sup> Deckared with any printer actual with any entry inter and sparse printed and other factors. <sup>9</sup> Deckared with any entry inter and sparse printed and other factors. <sup>9</sup> Deckared with any entry inter and vield with any entry inter <sup>9</sup> with any entry inter and sparse printed and other factors. <sup>9</sup> Deckared with any entry inter and sparse printed and other factors. <sup>9</sup> Deckared with any entry inter and sparse printed and other factors. <sup>9</sup> Deckared with any entry inter and sparse printed and other factors. <sup>9</sup> Deckared with any entry inter and search of the fattors are considerable to a considerable to any entry entry inter and search or the fattors are considerable and other factors. <sup>9</sup> Deckared with any entry inter and search printer and under factors are considerable in approximates of the printer and search with any entry interes and any entry interes and and other factors are available in a constance with sparse printed and other factors are available in a constance with sparse printed and other factors are available in a constance with sparse printed and other factors are available and printer and searce to any entry engline additional printerable and entry interes and entry interes and entry interes



© Cogyright 2021 HP Development Company, LP. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. November 2021

overnoer 2021